Horn-coupled, commercially-fabricated aluminum lumped-element kinetic inductance detectors for millimeter wavelengths

H. McCarrick, D. Flanigan, G. Jones, B. R. Johnson, P. Ade, D. Araujo, K. Bradford, R. Cantor, G. Che, P. Day, S. Doyle, H. Leduc, M. Limon, V. Luu, P. Mauskopf, A. Miller, T. Mroczkowski, C. Tucker, and J. Zmuidzinas

Citation: [Review of Scientific Instruments](#) **85**, 123117 (2014); doi: 10.1063/1.4903855

View online: <http://dx.doi.org/10.1063/1.4903855>

View Table of Contents: <http://scitation.aip.org/content/aip/journal/rsi/85/12?ver=pdfcov>

Published by the [AIP Publishing](#)

Articles you may be interested in

[Thin film dielectric microstrip kinetic inductance detectors](#)

Appl. Phys. Lett. **96**, 102504 (2010); 10.1063/1.3314281

[Analysis of the acoustoelectric behavior of microwave frequency, temperature-compensated AlN-based multilayer coupling configurations](#)

J. Appl. Phys. **104**, 104509 (2008); 10.1063/1.3028231

[Position sensitive x-ray spectrophotometer using microwave kinetic inductance detectors](#)

Appl. Phys. Lett. **89**, 222507 (2006); 10.1063/1.2390664

[Radio frequency SQUIDs operating at 77 K with 1 GHz lumped-element tank circuits](#)

Appl. Phys. Lett. **72**, 969 (1998); 10.1063/1.120611

[Optimizing the two-coil mutual inductance measurement of the superconducting penetration depth in thin films](#)

J. Appl. Phys. **82**, 3028 (1997); 10.1063/1.366287

Confidently measure down to 0.01 fA and up to 10 PΩ

Keysight B2980A Series Picoammeters/Electrometers

[View video demo](#)

Horn-coupled, commercially-fabricated aluminum lumped-element kinetic inductance detectors for millimeter wavelengths

H. McCarrick,^{1,a)} D. Flanigan,¹ G. Jones,¹ B. R. Johnson,¹ P. Ade,² D. Araujo,¹ K. Bradford,³ R. Cantor,⁴ G. Che,³ P. Day,⁵ S. Doyle,² H. Leduc,⁵ M. Limon,¹ V. Luu,¹ P. Mauskopf,^{2,6} A. Miller,¹ T. Mroczkowski,^{7,b)} C. Tucker,² and J. Zmuidzinas^{5,8}

¹*Department of Physics, Columbia University, New York, New York 10025, USA*

²*School of Physics and Astronomy, Cardiff University, Cardiff, Wales CF24 3AA, United Kingdom*

³*Department of Physics, Arizona State University, Tempe, Arizona 85287, USA*

⁴*STAR Cryoelectronics, Santa Fe, New Mexico 87508, USA*

⁵*Jet Propulsion Laboratory, Caltech, Pasadena, California 91109, USA*

⁶*Department of Physics and School of Earth and Space Exploration, Arizona State University, Tempe, Arizona 85287, USA*

⁷*Naval Research Laboratory, Washington DC 20375, USA*

⁸*Department of Physics, Caltech, Pasadena, California 91125, USA*

(Received 25 July 2014; accepted 27 November 2014; published online 30 December 2014)

We discuss the design, fabrication, and testing of prototype horn-coupled, lumped-element kinetic inductance detectors (LEKIDs) designed for cosmic microwave background studies. The LEKIDs are made from a thin aluminum film deposited on a silicon wafer and patterned using standard photolithographic techniques at STAR Cryoelectronics, a commercial device foundry. We fabricated 20-element arrays, optimized for a spectral band centered on 150 GHz, to test the sensitivity and yield of the devices as well as the multiplexing scheme. We characterized the detectors in two configurations. First, the detectors were tested in a dark environment with the horn apertures covered, and second, the horn apertures were pointed towards a beam-filling cryogenic blackbody load. These tests show that the multiplexing scheme is robust and scalable, the yield across multiple LEKID arrays is 91%, and the measured noise-equivalent temperatures for a 4 K optical load are in the range $26 \pm 6 \mu\text{K}\sqrt{\text{s}}$. © 2014 AIP Publishing LLC. [<http://dx.doi.org/10.1063/1.4903855>]

I. INTRODUCTION

In this paper we present the design and measured performance of horn-coupled, aluminum lumped-element kinetic inductance detectors (LEKIDs). These devices were designed for cosmic microwave background (CMB) studies,^{1,2} so they operate in a spectral band centered on 150 GHz, which is where the CMB frequency spectrum peaks. Our LEKID design is scalable to higher frequencies, so these devices could be used for a range of millimeter-wave and sub-millimeter-wave activities. The detectors were fabricated in industry, which is a unique aspect of this study. To date, millimeter-wave detectors for CMB studies have exclusively been fabricated in government laboratories or at universities. Here, we report the performance of the first generation of our commercially-fabricated devices.

LEKIDs are superconducting thin-film resonators also designed to be photon absorbers. Absorbed photons with energies greater than the superconducting gap break Cooper pairs, changing the density of quasiparticles. The quasiparticle density affects the kinetic inductance and dissipation of the superconducting film, so a changing optical signal will cause the resonant frequency and internal quality factor of the resonator to shift. These changes in the properties of the resonator can be detected as changes in the amplitude and phase

of a probe tone that drives the resonator at its resonant frequency. This detector technology is particularly well-suited for sub-kelvin, kilo-pixel detector arrays because each detector element can be dimensioned to have a unique resonant frequency, and the probe tones for hundreds to thousands of detectors can be carried into and out of the cryostat on a single pair of coaxial cables.

Current experiments focused on studying the CMB polarization anisotropies use arrays of thousands of detectors. Transition edge sensor (TES) bolometers are the current detector standard for these studies. In general, TES devices are composed of a photon absorber suspended by a weak thermal link. The absorber temperature is related to the incident photon power, and this temperature is detected with a superconducting temperature sensor and read out with a superconducting quantum interference device (SQUID). The operational details of these detectors are thoroughly described in the literature.³ A variety of TES architectures have already been deployed for CMB studies.^{4–9} The next generation of CMB experiments will require an even greater number of detectors for improved sensitivity. The inherent scalability of LEKIDs makes them a potential candidate for these future CMB measurements, so we conducted the study we describe here to explore this hypothesis further.

Microwave kinetic inductance detectors (MKIDs) were first published in 2003,¹⁰ and the lumped-element MKID variety was published in 2008.¹¹ Over the past decade, a number of groups around the world have pursued MKID

^{a)}Electronic mail: hlm2124@columbia.edu

^{b)}National Research Council Fellow.

technologies for a variety of astrophysical studies at different wavelengths, and our work builds from this experience. Experiments that have deployed or plan to use MKID-based cameras include ARCONS,¹² MAKO,¹³ MicroSpec,¹⁴ MUSIC,¹⁵ NIKA,¹⁶ BLAST-TNG,¹⁷ and SuperSpec.¹⁸ Laboratory studies show that state-of-the-art LEKID designs can achieve photon noise limited performance,^{13,19} and photon noise limited horn-coupled LEKIDs sensitive to 1.2 THz were recently demonstrated.²⁰

The fundamental detector performance goal for CMB studies is to reduce the intrinsic detector noise so that it is negligible when compared with the noise due to the arrival statistics of the photon background. The detector performance reported in this paper is consistent with photon noise limited performance. LEKID noise has been extensively studied, and it includes contributions from three sources: generation-recombination (g-r) noise, amplifier noise, and two-level system (TLS) noise. These noise sources are thoroughly described in the literature.²¹ The generation-recombination noise is due to fluctuations in the quasiparticle number from recombination into Cooper pairs and from thermal generation of quasiparticles. Under typical loading conditions, this noise is caused mostly by randomness in the recombination of optically excited quasiparticles, and the thermal generation of quasiparticles is negligible. The amplifier noise is the electronic noise of the readout system referred to the detector array. It is set by the noise figure of the cryogenic microwave low-noise amplifier (LNA) immediately following the detectors. TLS noise is produced by dielectric fluctuations due to quantum two-level systems in amorphous materials near the resonators. The scaling of TLS noise with the operating temperature, probe tone power, resonant frequency, and geometry of the capacitor has been extensively studied experimentally.²² This knowledge has been captured in a semi-empirical noise model, which gives us the ability to make empirically-grounded predictions of the TLS noise we should expect for a given capacitor and inductor design.²² We designed our detectors using this semi-empirical model for the range of optical loads that are typical for ground-based and sub-orbital CMB experiments.

The remainder of the paper is organized in the following way. In Sec. II we present the design of the horns and the detectors. This section also describes the experimental set up, including the cryogenic system and the detector readout. In Sec. III, we present measurements of the LEKIDs with and without optical loading. In Sec. IV, we summarize our design and measurement results and describe our future plans. One goal of this paper is to provide a detailed end-to-end description of our design and testing process, which could be useful for uninitiated readers or groups interested in starting to make LEKIDs. For clarity, in many places we provide the equations and other bits of practical information collected from the literature that were essential to our design and analysis process.

II. METHODS

We designed and built a prototype 20-element, horn-coupled LEKID module that is sensitive to a spectral band centered on 150 GHz. The module consists of a LEKID array

on a silicon chip and an aluminum horn package. The LEKIDs were fabricated in the foundry at STAR Cryoelectronics in New Mexico. The aluminum horn package was manufactured in the Micromachining Laboratory at Arizona State University. The modules were designed, assembled and tested at Columbia University. For LEKIDs, the various construction parameters must simultaneously satisfy both the requirements of the resonator circuit and the optical coupling to millimeter-wavelength radiation. It is instructive to first describe the photon coupling design (Sec. II A) and then describe the resonator circuit (Sec. II B).

A. Optical coupling design

Our design uses horn-coupled detectors for a number of reasons. First, the horn beam reduces sensitivity to stray light inside the cryostat and couples well with the telescope optics in instruments we are developing.^{1,2} Second, the waveguide in the horn provides an integrated high-pass filter. Third, the horn pitch creates space for the large interdigitated capacitor, which allows for resonant frequencies below 250 MHz and reduces the effects of TLS noise. Finally, electrical cross-talk is reduced because the final configuration is not tightly packed.

A cross-sectional view of one array element and a schematic of one detector are shown in Figure 1, a photograph of a device is shown in Figure 2, and the detector module is shown in Figure 3. The conical horn flare narrows down to a single-mode cylindrical waveguide section, which defines the low-frequency edge of the spectral band at 127 GHz. The high-frequency edge is defined by a quasi-optical metal-mesh low-pass filter. The waveguide is then re-expanded with a second conical flare to reduce the wave impedance at the low-frequency edge of the spectral band, which improves optical coupling and allows the radiation to be launched efficiently into the subsequent dielectric stack. The dielectric stack is composed of an approximately quarter-wavelength layer of fused silica (300 μm) and the silicon wafer (300 μm). The fused silica helps match the wave impedance to the silicon substrate. The radiation launched from the waveguide remains fairly well collimated as it travels through the dielectric stack and back-illuminates the inductor/absorber, which is patterned on the silicon and dimensioned to match the wave impedance. There is a metal cavity behind each detector that is a quarter wavelength deep that acts as a back-short. The dielectric stack is mounted directly to the horn plate using a spring-loaded aluminum clip. The aluminum clip provides force that increases the thermal conductivity at the interface between the dielectric stack and the horn plate. A metal back plate, with the back-short cavities, is attached to seal the module. Electromagnetic simulations using the Ansoft HFSS software package predict that the maximum coupling efficiency to a single-polarization for this design is 90% and averages >70% over the 130–170 GHz band, as shown in Figure 1.

The conical flare produces a very small mixing of electromagnetic modes from the small aperture TE₁₁ to the exit aperture into the quartz of less than 1%. There will be some reflection at the exit aperture and at the interface between the quartz and silicon and also at the detector. The electromag-

FIG. 1. (a) A schematic of a single LEKID. The meandered inductor in the resonator is also the photon absorbing element. The interdigitated capacitor (IDC) completes the resonant circuit. The resonator is capacitively coupled to a transmission line, which carries the probe tone that is used to read out the detector. (b) Cross-sectional view of a single array element showing the horn plate, the dielectric stack, one LEKID, and the back-short plate. For clarity, this schematic is not drawn to scale. (c) Diagram of a single resonator circuit. The resonator is capacitively coupled (C_c) to the transmission line with impedance Z_0 . The resonant frequency is set by the total inductance $L = L_g + L_k$, where L_g is the geometric inductance and L_k is the kinetic inductance, along with the capacitance C of the interdigitated capacitor. An absorbed photon changes the quasiparticle density in the device and thus L_k , resulting in a resonant frequency shift, which is read out using a probe tone near the resonant frequency. (d) Electromagnetic simulation results show the absorptance as a function of frequency for the horn-coupled aluminum LEKID design. The dotted-dashed line shows the single-polarization absorptance spectrum for the inductor/absorber using the nominal design value of $1.2 \Omega/\square$ resistivity for aluminum. The solid line shows the simulated absorptance spectrum for the measured resistivity of the devices, $4 \Omega/\square$, which has an average absorptance of 72% across the single-mode spectral band. The dashed line is the measured transmittance spectrum of the metal-mesh low-pass filter, used to define the upper edge of the spectral band. The inset shows the simulation set up and the simulated current density over the absorbing area.

netic simulations of the coupling to the detector, shown in Figure 1, take all of these effects into account by launching a single mode (or one for each polarization) from the single mode circular waveguide section and then computing the electric field through the rest of the structure including the conical flare, the dielectric layers, the aluminum LEKID and the backshort. No resonances are seen in the band where the detector operates in part due to absorption of power by the aluminum and damping of any resonances. The size of the detector is large enough that it can effectively absorb multiple modes of incident electromagnetic radiation.

B. Detector design

The detectors are designed to have the following properties: high absorptance and responsivity, low detector noise, and optimal electrical coupling. The overall design of the detector requires balancing competing constraints on various construction parameters. In the following paragraphs we describe the design of the inductor, which largely controls the absorptance and responsivity, the capacitor geometry, which influences the TLS noise, the transmission line, and the electrical coupling.

FIG. 2. Photomicrographs of a single LEKID. All components are fabricated from thin-film aluminum with a single mask.

The detector array consists of back-illuminated LEKIDs fabricated from a 20 nm thick aluminum film deposited on a 300 μm thick high-resistivity ($>10 \text{ k}\Omega\text{cm}$), float-zone silicon substrate. The inductor/absorber is a meandered aluminum trace on silicon with a filling factor of 1.5%, calcu-

lated as the inductor trace width divided by the gap width plus trace width. This filling factor is designed to match the wave impedance of the incoming radiation in silicon, which has a dielectric constant, $\epsilon_r = 11.9$ and a wave impedance of $\sim 110 \Omega$. The effective impedance of the inductor is Z_{eff}

FIG. 3. (a) Photograph of a 20-element LEKID array. The LEKID inductors have a 4.8 mm hexagonal pitch, and the varying sizes of the interdigitated capacitors are evident. (b) The LEKID array mounted to the aluminum horn plate with the spring-loaded clip. The horn apertures are facing down and therefore not visible in this photograph. (c) The fully-assembled detector package with the conical horns facing up. For clarity, the low-pass filter, which is normally attached directly to the horn array using the four visible tapped holes, was removed for this photograph. (d) The cryogenic test setup. The detector package is mounted to the 100 mK stage. The Eccosorb is the optical load for this study, and the Eccosorb temperature was adjusted with the heater resistor. The load is mechanically mounted to the 1.5 K stage with thermally isolating G10 legs and thermally connected to the 3 K stage with a copper wire, so the base temperature of the optical load should closely track the temperature of the 3 K stage. The indicated waveguide, horn, and optics box are elements of a second kind of load, which is under development and will be used in future studies.

$\approx (\rho g_L)/(w_L t)$, where t is the film thickness, g_L is the gap width between meanders, w_L is the meander width, and ρ is the material resistivity, for which we used the typical value for 20 nm thick aluminum, $1.2 \Omega/\square$.

To efficiently absorb incident photons and approximate a solid sheet, the pitch between the inductor meanders should be less than $\lambda/20$ where λ is the incident wavelength.²³ The choice of a $2 \mu\text{m}$ wide trace and $125 \mu\text{m}$ spacing between meanders, gives an effective sheet impedance of 76Ω with a 15% efficiency loss, using the standard value for 20 nm thick aluminum resistivity. Although this does not perfectly match the wave impedance in the silicon, the absorption is not particularly sensitive to this parameter. In Figure 1, electromagnetic simulations using the HFSS software package show the detector absorption using both the nominal design resistivity and the measured resistivity of the devices, $4 \Omega/\square$. Electromagnetic simulations also show that the incident radiation spreads preferentially in the direction perpendicular to the E-field and thus the inductor/absorber has dimensions of $2 \times 3 \text{ mm}$.

In addition to absorbing the incident photons, the inductor is also part of the resonator circuit. Thus, the meandered inductor must be carefully designed to match the wave impedance of the incident photons yet have a high kinetic inductance fraction, $\alpha_k = L_k/(L_k + L_g)$. The kinetic inductance can be predicted using

$$L_k = \frac{A_L}{w_L(w_L + g_L)} \frac{h R_s}{2\pi^2 \Delta}, \quad (1)$$

where w_L is the width of the inductor trace, A_L is the total area of the inductor, R_s is the normal surface resistance, h is the Planck constant, and Δ is the gap energy, defined as²⁴ $\Delta \approx 1.76 k_B T_c$. Here, T_c is the superconducting transition temperature and k_B is the Boltzmann constant. The first term in the expression is simply the number of squares of material and the second term in the expression is the kinetic surface inductance L_s . The value for the geometric inductance was obtained from electromagnetic simulations using the Sonnet software package. Practical fabrication constraints with a contact mask limit the film thickness to approximately 20 nm and the trace width to approximately $2 \mu\text{m}$. For a 20 nm thick by $2 \mu\text{m}$ wide aluminum trace, the predicted $L_k \approx 35 \text{ nH}$ and $\alpha_k \approx 0.4$.

Fluctuations in the absorbed optical power are proportional to fluctuations in the total quasiparticle number N_{qp} and as such, fluctuations in the quasiparticle density $n_{qp} = N_{qp}/V_L$ are inversely proportional to inductor volume. Thus, for a given optical load, decreasing the volume of the inductor increases the responsivity. Given the above constraints, the inductor volume is $V_L = 1870 \mu\text{m}^3$. The geometric inductance of the resulting design is approximately 59 nH.

Changes in the quasiparticle density in the resonator cause changes in both the resonant frequency and the quality factor, which is related to the internal dissipation. These changes cause deviations of the complex transmission in orthogonal directions, which are referred to as the frequency and dissipation directions. Two-level systems produce noise only in the frequency direction.^{25,26}

Suppressing the TLS noise has historically been challenging. Gao *et al.*²² have shown that TLS noise scales with the capacitor digit gap widths as $g_{IDC}^{-1.6}$, and thus we want to

FIG. 4. The detectors are coupled to a feed line which runs down the center of the array and has tines that distribute the probe tones to the individual LEKIDs.

maximize the gap widths. We also chose to target resonant frequencies below 200 MHz to match the baseband bandwidth of the readout system, avoiding the need for mixers. Using a low readout frequency allows us to fit more detectors in a given bandwidth. Lower readout frequencies should in theory couple less strongly to the TLS fluctuators in the resonators, thus reducing their impact.²¹ To simplify modeling, we imposed the constraint on the interdigitated capacitors that the digit widths and the gaps between them be of equal size.²⁷ We maximized the gap widths, while maintaining a resonant frequency less than 200 MHz using the available area as determined by the horn and detector pitch. The resulting capacitor geometry has a gap width of $8 \mu\text{m}$. The area of the largest capacitor is 9 mm^2 . The capacitors have values in the range of 6–28 pF.

The resonators are capacitively coupled to the transmission line, which carries the probe tones. We use an aluminum transmission line structure that has a central trace across the array and tines which distribute the signal to the individual detectors, as shown in Figure 4. The transmission line structure acts as a lumped element as its length is much less than the wavelength of the readout frequencies. Ground returns for the resonators are provided by similar tines coming from aluminum strips at the sides of the chip, which are wire bonded to the package. The central transmission line is a trace $20 \mu\text{m}$ wide. The tines are $15 \mu\text{m}$ wide. We chose these widths based on simulations, which show that the transmission line is matched to 50Ω across the readout bandwidth at the interfaces with the rest of the readout chain.

To achieve sufficient coupling at these low resonant frequencies we used interdigitated capacitors between the resonator and both the signal tine and the ground return tine. This coupling design is schematically shown in Figure 1.

Electromagnetic simulations were used to verify this coupling scheme. To maximize responsivity, the coupling quality factor Q_c should equal the internal quality factor Q_i under the expected optical load.²¹ To calculate the necessary coupling capacitance we begin with the definition of the quality factor

$$Q \equiv \frac{2\pi f_0 E}{P_d}, \quad (2)$$

where E is the peak energy stored in the resonator, f_0 is the resonant frequency, and P_d is the average power dissipation. During the phase of the oscillation when the resonator energy is completely stored in the capacitor, we can write the coupling quality factor Q_c as

$$Q_c = \frac{2\pi f_0}{P_d} \left(\frac{1}{2} C |V|^2 \right), \quad (3)$$

where P_d is the power dissipated from the resonator into the load impedance Z_0 across the coupling capacitor, C is the capacitance of the main capacitor in the resonator, and V is the peak voltage across the resonator. The power dissipated in the load through the coupling capacitor is then

$$P_d = \frac{1}{2} |I|^2 \frac{Z_0}{2}, \quad (4)$$

where I is the current that flows through the coupling capacitor, C_c . Since $1/(2\pi f_0 C_c) \gg Z_0$, and taking into account the fact that there are two coupling capacitors in series, we can write

$$P_d = \frac{1}{2} \left| V \frac{2\pi j f_0 C_c}{2} \right|^2 \frac{Z_0}{2}. \quad (5)$$

Finally, by substituting Eq. (5) into Eq. (3), we arrive at

$$C_c = \sqrt{\frac{8C}{2\pi f_0 Q_c Z_0}}, \quad (6)$$

and for the optimal coupling of this design we set $Q_c = Q_i = 10^5$. Thus, the coupling capacitors are designed to have C_c values between 0.06 and 0.25 pF.

C. Detector fabrication

The wafers were processed at STAR Cryoelectronics using standard photolithographic procedures. First, the wafers were cleaned with acetone, isopropyl alcohol, and deionized water. A plasma ashing was used to remove any residual organic material. An argon plasma was then used to remove SiO_2 from the surface of the wafer. The aluminum film was deposited through evaporation. The wafers go through standard lithography: application of hexamethyldisilazane (HMDS) to promote resist adhesion, dehydration bake, resist coat, soft bake, resist exposure, resist developing, hard bake, descum, and finally ion milling is used to etch away the unwanted aluminum. We used a standard contact mask for patterning the aluminum. The resist was then stripped using acetone, isopropyl alcohol, deionized water, and plasma ashing, put in vacuum to dehydrate, coated with HMDS, and finally a protective resist layer is applied to protect the devices while dicing. Photomicrographs of the fabricated devices are shown in Figure 2.

A common technique used for MKID fabrication on silicon is to dip the wafer in a hydrofluoric acid bath before processing. This etches away any SiO_2 and hydrogen-terminates the silicon, protecting it from further oxidation. This step can help reduce TLS effects. We have fabricated additional devices including this step, the results of which we will describe in a future paper.

D. Experimental setup

The detectors are cooled in a DRC-102 ADR Cryostat System made by STAR Cryoelectronics. This cryostat system uses a Cryomech PT407 Pulse Tube Cooler and a two-stage adiabatic demagnetization refrigerator (ADR), which provides 112 mJ of cooling capacity for the 100 mK stage. The working end of the cryostat is shown without radiation shields in Figure 3.

All of the detectors in the module are frequency-multiplexed in a readout band between 80 and 160 MHz, and read out with a single SiGe bipolar cryogenic low-noise amplifier (LNA) and one pair of coaxial cables.²⁸ Here we describe in detail the path of the probe tones, shown schematically in Figure 5. To minimize the loading from the coax on the 4 K stage, a 1 m long 2.16 mm (85 mil) diameter stainless steel inner and outer conductor coax (SSI Cable Corps UT085-SS) runs from ambient temperature to 4 K, intercepted at the 45 K stage. DC blocks (Inmet 8040) provide thermal breaks for the center conductor of the coax at the 45 K and 4 K stages. After the DC block, a -20 dB attenuator (Inmet GAH-20) reduces any 300 K radiation propagating down the coax, dissipating the power at the 4 K stage. A 60 cm long section of 0.86 mm (34 mil) diameter cupronickel (CuNi) coax (Coax Co. SC-033/50-CN-CN²⁹) carries the signal from 4 K to another -20 dB attenuator mounted on the 100 mK stage which reduces the noise contribution from the 4 K stage attenuator. We originally used an Anritsu 43KB-20 for the coldest attenuator, which had good performance, but started superconducting around 500 mK, rendering it unsuitable for this application. A short length of semi-rigid copper coax brings the signal from a second attenuator on the 100 mK stage to the cooled package. The copper coax terminates in an SMA connector on the package, which is soldered to a gold-plated microstrip interface board made from Duroid 6010 ($\epsilon_r = 10.8$). Aluminum wire bonds connect the microstrip to the detector array, and explicitly connect the ground return of the detectors to the package.

On the return path, a 50 cm long superconducting NbTi coax (Coax Co. SC-033/50-NbTi-NbTi) carries the signal from 100 mK to 4 K, which has both extremely low thermal conductivity and low loss.³⁰ The signal is then amplified by the LNA (Caltech LF-2), with a noise temperature, $T_N < 5$ K, over the array bandwidth. The gain of the LNA is sufficiently high that the noise temperature of the cascaded readout chain is dominated by that of the LNA, which itself is subdominant to the noise of the detector. Stainless steel coax carries the signal from 4 K to 45 K and finally to 300 K, with a DC block at the 45 K stage.

FIG. 5. A block diagram of the probe tone signal chain.

1. Digital readout

Detector data were collected with a digital readout system called CUKIDS that was developed at Columbia University. This system uses the CASPER signal processing tool flow, a ROACH field-programmable gate array (FPGA) board,³¹ and the 12-bit analog-to-digital converter and 16-bit digital-to-analog converter (DAC) card developed for the MUSIC instrument.³² The room temperature analog signal conditioning consists of amplifiers, low-pass filters, and digital step attenuators from Mini-Circuits, Inc. The readout firmware, control, and analysis software we developed is open-source and available online.³³

Currently, the system is optimized for laboratory testing, essentially providing multiple homodyne test setups in parallel. The probe tone waveforms are generated using a circular playback buffer feeding the DAC. After digitization, the signal is channelized using a polyphase filterbank (PFB). The complex voltage waveforms from the PFB channels that contain the probe tones are sent to the host computer for storage and analysis. All subsequent demodulation and analysis is done offline. For the measurements reported here, the FPGA was configured to provide four simultaneous homodyne readouts, each with a bandwidth of 125 kHz.

2. Blackbody load

For this study, we designed and built the cryogenic test setup shown in Figure 3. This setup includes a blackbody load that has a temperature range from less than 4 K to 6 K. In its coldest state, it should look similar to the CMB. The selected loading range is similar to those that are expected for ground-based and sub-orbital experiments. We use the variable temperature load to directly calibrate our detector noise and responsivity.

The blackbody is constructed from a slab of 6.35 mm (0.25 in.) thick Eccosorb MF-110 absorber coated with a 0.4 mm (0.015 in.) thick sheet of etched Teflon for impedance matching. The etched Teflon is bonded to the Eccosorb with a thin layer of Stycast 2850FT. We designed this load using loss

tangent and refractive index information from the literature.³⁴ The emissivity of the load is calculated to be 92%.

The Eccosorb slab is mounted to a copper thermal bus, and this assembly is mechanically supported by G-10 legs that are connected to the 1.5 K ADR stage. The temperature of the Eccosorb is controlled using a weak thermal link to the 4 K pulse-tube cooler stage and a heater resistor, which is mounted on the copper thermal bus. We designed the thermal time constant of the blackbody source to be approximately 20 min to minimize the required heat input while still providing a reasonably short settling time when changing temperatures. The blackbody is <1 cm from the detector module, and the entire setup is enclosed in a 4 K shield. There is also a copper shield surrounding the detector module to minimize light leaks. This shield is attached to the 100 mK stage, and it has an aperture exposing the low-pass filter.

III. RESULTS

We performed a range of experiments to measure the quality of the fabricated detectors, the results of which are presented in Secs. III A–III C. We first report the electrical properties of the film, followed by measurements of the detectors themselves in a dark environment. We describe in detail the fitting procedure used to analyze the data. The data are compared to Mattis-Bardeen theory. We then proceed to optical testing with the blackbody load described above, which provides measurements of the optical responsivity and noise.

A. Film properties

To ascertain the residual resistance ratio (RRR) and the superconducting transition temperature T_c of the aluminum film, we performed a four-wire measurement of the resistance of a $2 \mu\text{m} \times 35\,000 \mu\text{m}$ meandered trace as a function of temperature. This witness sample was made alongside the LEKIDs on the same silicon wafer and therefore from the same 20 nm thick aluminum film. The resistance of the sample at 3 K is 70 k Ω , yielding a surface resistance of 4.0 $\Omega/\square$. The resistance at 300 K is approximately 210 k Ω , giv-

ing a measured RRR of 3.3. We measured $T_c = 1.46$ K, which agrees well with the T_c measured independently by the probe tones at the ~ 100 MHz readout frequencies. Other measurements of thin-film aluminum in the literature³⁵ also report values of the critical temperature higher than that of bulk aluminum, which is nominally 1.2 K.

B. Dark testing

Initial characterization of the resonators is done in a “dark” package, which is sealed with metal tape to minimize light leaks. Frequency sweeps through the resonances taken at different bath temperatures can be fit to determine the resonant frequencies and quality factors as a function of temperature. Frequency sweeps are done at a variety of probe tone powers to determine the maximum readout power at which the detector can be operated before the device response becomes nonlinear due to the nonlinear kinetic inductance effect.³⁶ The bifurcation power is found to be around -100 dBm across the array. This is approximately 10 dB higher than predicted using the theory described by Swenson *et al.*,³⁶ assuming that the nonlinearity energy scale E_* is equal to the condensation energy of the inductor $E_{\text{cond}} = N_0 \Delta^2 V_L / 2$, which is expected to be the case if $\alpha_k \approx 1$. Here N_0 is the single-spin density of states at the Fermi level. Approximately 4 dB of this discrepancy can be explained by the fact that $\alpha_k \approx 0.66$. In addition, as Swenson *et al.*³⁶ point out, it is difficult to directly compare E_{cond} to the value of E_* implied by measurements because the absolute power in the inductor is influenced by unknown temperature dependent loss in the cryogenic cabling and by mismatches between the transmission line and the resonator. The measurements reported here were taken with a readout power of approximately -111 dBm, well below bifurcation, except where otherwise noted.

1. Yield

Overall, we have tested a total of three 20-element arrays and two 9-element arrays all made on the same wafer. We have found 71 working resonators of the total 78, corresponding to an overall yield fraction of $\sim 91\%$. Subsequent test results focus on a single 20-element array. The resonant frequencies were designed to fall between 100 and 200 MHz. We found that all were systematically shifted down in frequency by about 15%. This frequency shift is reasonably well explained when the kinetic inductance is calculated using the measured surface resistance of $4 \Omega/\square$ and $T_c = 1.46$ K instead of the originally assumed $1.2 \Omega/\square$ and $T_c = 1.2$ K, giving an L_k of approximately 100 nH and a resonance frequency shift of approximately 20%. Lithographic tolerances (e.g., the under etching of the capacitor resulting in increased capacitance or a different film thickness than desired) could also be responsible for smaller shifts in the resonant frequency.

2. Resonator frequency sweep fitting

We fit the resonators using a model which takes into account the skew of the resonance caused by mismatches in the

transmission line.³⁷ At higher probe powers, we found it necessary to also incorporate the nonlinear model presented by Swenson *et al.*³⁶ The complete model for the complex forward transmission S_{21} as a function of frequency f is

$$S_{21}(f) = A e^{-2\pi j D f} \left(1 - \frac{Q_r / Q_e}{1 + 2j Q_r x} \right), \quad (7)$$

where $A = |A|e^{j\phi}$ is an arbitrary complex scale factor, D is the cable delay, Q_r is the loaded resonator quality factor, Q_e is the complex coupling quality factor, and x is the detuning parameter, which is simply $(f - f_0)/f_0$ in the case of the basic linear model, where f_0 is the resonant frequency. For the nonlinear bifurcation model, x is given by the solution to the cubic equation

$$y = y_0 + \frac{a}{1 + 4y^2}, \quad (8)$$

where $y_0 = (f - f_0)/f_0$, $x = y/Q_r$, and a is the bifurcation parameter defined by Swenson *et al.*³⁶ The solution to this cubic equation is given in the Appendix.

The real and imaginary parts of the model and data were fit simultaneously using the Levenberg-Marquardt algorithm for nonlinear least-squares minimization. We parameterized Q_e in terms of its real and imaginary components, which yielded more robust fits than using its magnitude and phase. By fitting both the real and imaginary parts of the model simultaneously, we found that the resulting fits were very well constrained, even with only a few data points spaced across the resonance. We used the `lmfit` Python package³⁸ which provides a convenient interface to the underlying algorithm. We also used the `emcee` package³⁹ to perform a Markov-Chain Monte Carlo analysis of the fits to ensure the errors were realistic.

3. Quality factors

We adopt the convention proposed by Khalil *et al.*,³⁷ defining the internal (unloaded) quality factor of the resonator as

$$Q_i^{-1} = Q_r^{-1} - \text{Re} Q_e^{-1}. \quad (9)$$

We define an effective real coupling quality factor $Q_c = (\text{Re}(Q_e^{-1}))^{-1}$.

The quality factors for the detectors measured in an aluminum package and a dark environment at 200 mK are greater than 5×10^5 as shown in Figure 6. The package is made of the QC-10 aluminum alloy,⁴⁰ which is easily machinable and known to superconduct in our operating temperature range. We had originally used a gold-plated copper package, but found that the internal quality factors were limited to $\sim 4 \times 10^4$, presumably due to coupling between the resonators and the lossy normal metal of the package.

The effective real coupling quality factors are $\sim 2 \times 10^5$ and match reasonably well to the design value. With no loading, the coupling quality factor limits the resonator quality factor. Under optical loading, however, the coupling is better matched. The resonator quality factors are sufficiently high that ~ 300 resonators can be read out in a single octave⁴¹ as

FIG. 6. Quality factors for the resonators measured at 200 mK in a dark environment. The internal quality factors are all greater than 5×10^5 . Here, Q_c refers to $(\text{Re}(Q_c^{-1}))^{-1}$. The errors on Q_r and Q_c are typically $\sim 1\%$, while the errors on Q_i are around 10%.

required for the proposed experiments. Additionally, the resonant frequencies of five detectors on the tested array were spaced such that greater than 300 resonators could be read out in a single octave. These resonators were all consistently functional and did not collide.

4. Bath temperature sweeps

The bath temperature of the detectors T is stepped in order to measure the device responsivity to thermal quasiparticles, to compare the device response to Mattis-Bardeen theory, and to look for signatures of TLS effects.

At each temperature, a frequency sweep of each resonator was measured and fit to Eq. (7) to extract the resonant frequency and quality factors. For each resonator, the fractional change in resonant frequency was computed as $x = (f - f_{\max})/f_{\max}$, where $f_{\max}$ is the maximum observed value of the resonant frequency for a resonator for the experiment.

At each temperature step and for each resonator a simultaneous fit was performed to the following two equations:

$$Q_{i,\text{total}}^{-1} = Q_{i,\text{MB}}^{-1} + Q_{\text{TLS}}^{-1} + Q_{\text{loss}}^{-1}, \quad (10)$$

$$x = x_{\text{MB}} + x_{\text{TLS}} + x_{\text{offset}}. \quad (11)$$

The terms in the expression for $Q_{i,\text{total}}^{-1}$ are the prediction from Mattis-Bardeen theory, the loss due to TLS, given below, and a constant loss term to account for effects such as radiation to free space or coupling to lossy materials near the device, which do not depend strongly on temperature.

In the following equations, we generally follow the treatment in Noroozian.⁴² The equations assume that the film is thin, that $hf \ll \Delta$, and that $k_B T \ll \Delta$. All of these assumptions are well satisfied for our devices. Using these assumptions, $Q_{i,\text{MB}}$ is given by

$$Q_{i,\text{MB}} = \frac{2N_0\Delta}{\alpha_k S_1 n_{qp}}, \quad (12)$$

where α_k is the kinetic inductance fraction, N_0 is the single-spin density of states at the Fermi level (1.72

$\times 10^{10} \mu\text{m}^{-3} \text{eV}^{-1}$ for aluminum⁴³), n_{qp} is the quasiparticle density, and

$$S_1 \approx \frac{2}{\pi} \sqrt{\frac{2\Delta}{\pi k_B T}} \sinh\left(\frac{hf}{2k_B T}\right) K_0\left(\frac{hf}{2k_B T}\right), \quad (13)$$

expresses the frequency and temperature dependence. Here K_0 is the modified Bessel function of the second kind. When operating our detectors at 200 mK, S_1 ranges from about 0.075 to 0.15 across our readout band. For these dark measurements, we can substitute the thermal quasiparticle density given by⁴³

$$n_{qp,\text{thermal}} \approx 2N_0 \sqrt{2\pi k_B T \Delta} \exp\left(-\frac{\Delta}{k_B T}\right) \quad (14)$$

into Eq. (12) to obtain

$$Q_{i,\text{MB}} \approx \frac{\pi}{4\alpha_k} \frac{e^{\Delta/(k_B T)}}{\sinh\left(\frac{hf}{2k_B T}\right) K_0\left(\frac{hf}{2k_B T}\right)}. \quad (15)$$

The loss due to TLS is represented by the product of a geometrical filling factor F_{TLS} , and a loss tangent δ_{TLS} .²⁶

$$Q_{\text{TLS}}^{-1} = F_{\text{TLS}} \delta_{\text{TLS}}. \quad (16)$$

The TLS loss tangent depends on temperature and electric field as

$$\delta_{\text{TLS}} = \delta_0 \tanh\left(\frac{hf}{2k_B T}\right) \left[\frac{1}{\sqrt{1 + |E/E_c|^2}} \right], \quad (17)$$

where δ_0 is the loss tangent at zero temperature and zero field, E is the electric field (which is related to readout power), and E_c is the critical field for TLS saturation, defined by Gao *et al.*²⁵ Since the measurements described in this section were all taken at a fixed readout power and the quality factor does not change appreciably below 300 mK where TLS effects are dominant, the electric field in the resonator E should be roughly constant, so we can treat the electric field dependence term as a constant. Since this constant is guaranteed to be less than one, we simply take it to be equal to one to obtain lower limits on δ_{TLS} . While F_{TLS} can be estimated from electromagnetic simulations, the measurements here cannot disentangle its value from δ_0 , so we treat the product as a single parameter in the fit.

The terms in the model for the frequency shift are the prediction from Mattis-Bardeen theory, the effect of TLS, and a constant offset x_{offset} , which is added for convenience to take into account the fact that the reference frequency to which the fractional change is measured is arbitrary. The prediction for the fractional frequency shift from Mattis-Bardeen theory is given by

$$x_{\text{MB}} = -\frac{\alpha_k S_2}{4N_0 \Delta} n_{qp}, \quad (18)$$

where

$$S_2 \approx 1 + \sqrt{\frac{2\Delta}{\pi k_B T}} \exp\left(-\frac{hf}{2k_B T}\right) I_0\left(\frac{hf}{2k_B T}\right). \quad (19)$$

Here I_0 is the modified Bessel function of the first kind. When operating our detectors at 200 mK, S_2 is approximately

3.8 across our readout band. For these dark measurements we again substitute the equation for the thermal quasiparticle density from Eq. (14) to obtain

$$x_{\text{MB}} \approx -\frac{\alpha_k}{4N_0\Delta} \left[1 + \sqrt{\frac{2\Delta}{\pi k_B T}} \exp\left(-\frac{hf}{2k_B T}\right) I_0\left(\frac{hf}{2k_B T}\right) \right] \times [2N_0\sqrt{2\pi k_B T \Delta} e^{-\Delta/(k_B T)}]. \quad (20)$$

The frequency shift induced by the temperature dependent TLS loss is

$$x_{\text{TLS}} = \frac{F_{\text{TLS}}\delta_0}{\pi} \left[\text{Re} \left[\Psi\left(\frac{1}{2} + \frac{hf}{2\pi j k_B T}\right) \right] - \log\left(\frac{hf}{k_B T}\right) \right] \times \left[\frac{1}{\sqrt{1 + |E/E_c|^2}} \right], \quad (21)$$

where Ψ is the complex digamma function. As before, we assume the electric field dependence term is equal to one and interpret the resulting $F_{\text{TLS}}\delta_0$ as a lower limit. Over the range of temperatures and readout frequencies we use, the term involving Ψ is essentially constant and approximately equal to $\text{Re}(\Psi(1/2)) \approx -1.96$.

In practice, there is a degeneracy between α_k and Δ . We first attempted to fix $\Delta = 1.76k_B T_c$ using $T_c = 1.46$ K as measured in Sec. III A. The resulting fits implied $\alpha_k \approx 0.35$, which is inconsistent with the measured resonance frequencies and film properties. Instead, we fixed $\alpha_k = 0.65$ using those measurements and found that the fits (shown in Figure 7) required that $T_c \approx 1.60$ K, or that $\Delta = 1.93k_B T_c$. Similarly elevated T_c -to- Δ conversion factors have been suggested for aluminum resonators in the literature.⁴⁴

The free parameters in the fit are then Δ , $F_{\text{TLS}}\delta_0$, $Q_{i,\text{loss}}^{-1}$, and the nuisance parameter x_{offset} . We fit the data using three variations of the model, as shown in Figure 7. First, we held $F_{\text{TLS}}\delta_0 = 0$ and $Q_{i,\text{loss}}^{-1} = 0$ and fit only the data above 250 mK, where the response should be well described by the pure Mattis-Bardeen theory. The resulting fit, shown as a solid green line, does indeed describe the data above 250 mK well, but it offers no explanation of the limited Q_i and non-monotonic “back-bending” behavior seen at lower temperatures. Next, we attempted to fit the full model including $F_{\text{TLS}}\delta_0$ and $Q_{i,\text{loss}}^{-1}$. The result is the dashed red line. Here, the “back-bending” in the frequency data dominates the fit, requiring a large value of $F_{\text{TLS}}\delta_0 \approx 1.4 \times 10^{-4}$, which implies more loss than is actually seen. Thus $Q_{i,\text{loss}}^{-1} = 0$ in this case. While this model does show “back-bending,” the shape is not exactly in agreement with the data. Others have reported similar discrepancies at low temperatures for TiN LEKIDs.³⁶ Previous studies of the temperature dependence of TLS have been made at much higher readout frequencies, where it is possible to probe the minimum in the x_{TLS} equation that occurs at $T = hf/(2k_B)$. For these devices, the temperature of this minimum is around 2.8 mK, which is not accessible with our cryostat. Finally, we held $F_{\text{TLS}}\delta_0 = 0$, and found that, aside from the “back-bending,” the limit to Q_i could be explained as a constant loss of $Q_{i,\text{loss}}^{-1} \approx 1.0 \times 10^{-6}$. This value is much more reasonable than the value implied for δ_0 implied by the TLS fit, but of course cannot explain the “back-bending.” This

FIG. 7. Bath temperature sweeps for a single resonator. The resonant frequency at 200 mK is 86.31195 MHz, and the probe power used was ~ -111 dBm. The plot in panel (a) shows the inverse internal quality factor, and the plot in panel (b) shows measurements of the fractional frequency change. Joint fits to the data for three models are plotted: Mattis-Bardeen theory alone (solid green), M-B with temperature-dependent TLS loss (dashed red), and M-B with a fixed loss term (dotted black). The x_{offset} parameter is also included in the models plotted in panel (b). For all models, α_k was fixed at 0.65, while T_c was allowed to vary. All fits resulted in $T_c \approx 1.60$ K, implying that the relationship between Δ and T_c is closer to $\Delta \approx 1.93k_B T_c$, assuming T_c is actually 1.46 K as measured in Sec. III A. The M-B theory provides a good fit to our data above 250 mK, particularly for the frequency response. The fit to the TLS model yielded $F_{\text{TLS}}\delta_0 \approx 1.4 \times 10^{-4}$, which is driven by the “back-bending” observed in the frequency response. The shape of this curve is inadequate to explain our data, so we do not place much confidence in this model, and hence the resulting value of $F_{\text{TLS}}\delta_0$ for our devices. The model with constant loss term fits the data reasonably well (yielding $Q_{i,\text{loss}}^{-1} \approx 1.0 \times 10^{-6}$) but does not explain the “back-bending” behavior.

residual loss could potentially be attributed to a residual, constant population of quasiparticles.

C. Optical testing

1. Quasiparticle lifetime

The response of the resonances in the readout bandwidth is limited by the resonator ring-down time $\tau_r = Q_r/(\pi f_0) \sim 300 \mu\text{s}$. It is thus difficult to measure the quasiparticle lifetime τ_{qp} using these resonances. We used a vector network analyzer to find higher-order resonances with lower quality factors so that the resonator bandwidth would be large enough to easily measure τ_{qp} . We targeted resonances with high enough quality factors such that the response to illumination was easily detectable. We read out these resonances with an analog homodyne setup.

We tested a 9-element array from the same wafer as the 20-element array. The array was mounted in a gold-plated copper package sealed with aluminum tape. The detectors were illuminated through small holes in the tape by a

FIG. 8. Measurements of a detector time constant as a function of bath temperature, extracted from fits to the time-domain response of a higher-order resonance to an LED pulse. Statistical error bars from the fitting process would be smaller than the data points. The solid black curve is a fit to Eq. (22) to the data, assuming a thermal quasiparticle density, and assuming $\Delta = 1.76k_B T_c$. The results are $\tau_{\max} = 488 \pm 16 \mu\text{s}$ and $n^* = 363 \pm 38 \mu\text{m}^{-3}$. If we instead assume $\Delta = 1.93k_B T_c$, as implied by the Mattis-Bardeen fits in Sec. III B 4, $n^* = 160 \pm 20 \mu\text{m}^{-3}$.

660 nm red LED coupled to a 2 mm diameter plastic fiber. We studied a resonance with a loaded quality factor of 6300 and a resonant frequency of 810 MHz.

We fit an exponential decay to the time-domain response to an LED pulse and found that the response was fit well by a single time constant. We measured this time constant as a function of bath temperature. As shown in Figure 8, the response time varied approximately as

$$\tau = \frac{\tau_{\max}}{1 + n_{qp, \text{thermal}}/n^*}, \quad (22)$$

where $n_{qp, \text{thermal}}$ is given by Eq. (14). This is the expected behavior of the quasiparticle lifetime.²¹

2. Responsivity

The temperature of the blackbody load, T_{bb} , is changed to measure the responsivity of the device to optically produced quasiparticles. In practice, T_{bb} ranged from 4 to 6 K, or approximately 1.7 to 3 pW for one mode with two polarizations over the 120 to 180 GHz band. The detectors are designed to be predominantly sensitive to a single polarization with an absorption efficiency $\eta_1 = 0.72$. The orthogonal polarization is expected to have $\eta_2 = 0.13$. Since our optical source is unpolarized, the predicted power absorbed by the detectors is calculated using a single mode with two polarizations, and the appropriate optical efficiencies are applied to each polarization. We refer to the total optical efficiency as η . For use in a polarimeter, there would be a polarization selective element, such as a wire grid, before the devices.

The measured response of a resonator as a function of optical loading is shown in Figures 9 and 10. The resonant frequency response is linear across the range of optical powers tested, and is about 40 ppm/K in all the devices.

FIG. 9. Resonance sweeps of a single resonator with changing optical load. The dots are measured points and the lines are fits. The resonant frequency at 200 mK is 86.31195 MHz. For these measurements the probe power was ~ -111 dBm, and the bath temperature was 200 mK. The measurement labeled 0.2 K was taken in the dark configuration.

If thermal quasiparticles are negligible, the quasiparticle density is¹³

$$n_{qp} = n^* \sqrt{1 + \frac{2\eta_{pb}\eta P_o \tau_{\max}}{\Delta V_L n^*}} - n^*, \quad (23)$$

where n^* is the film-dependent characteristic quasiparticle density,²¹ η_{pb} is the conversion efficiency (assumed to be ~ 0.7 over our band⁴⁵), P_o is the incident optical power, $\tau_{\max}$ is the maximum quasiparticle lifetime, h is the Planck constant, ν is the photon frequency, and V_L is the inductor volume. The incident optical power in a waveguide from a blackbody of temperature T_{bb} is

$$P_o = \int_{\nu_l}^{\nu_h} \frac{2h\nu^3}{c^2(e^{h\nu/kT_{bb}} - 1)} \frac{n}{\lambda^2} d\nu, \quad (24)$$

FIG. 10. Fitting the resonance curves shown in Figure 9 provides measurements of the resonant frequency as a function of blackbody temperature, plotted here as the fractional frequency change relative to the resonant frequency measured with the blackbody temperature at 4 K. Over the limited range of blackbody temperatures probed, the predicted response deviates by only a small amount from linear. The measured frequency response has a slope of approximately 40 ppm/K. This fractional responsivity is seen consistently across all resonators. The solid green line shows the expected response assuming $\tau_{\max} = 500 \mu\text{s}$, and $n^* = 400 \mu\text{m}^{-3}$, as suggested by the time constant measurements, and a total optical efficiency of $\eta = 0.14$. The dashed black line superimposed shows an alternative explanation for the data with the same value of $\tau_{\max}$, but with $n^* = 160 \mu\text{m}^{-3}$, which is closer to the typical value reported in the literature.²¹ In this case, $\eta = 0.32$.

where n is the number of dual-polarization modes, λ is the incident wavelength, and ν_l and ν_h are the low and high frequency edges of the spectral band. In this experiment the spectral band is defined by the waveguide cutoff at 130 GHz and the low-pass filter at 170 GHz.

The absorbed power is $P = P_o \eta$, where η is the absorption efficiency of the device. The frequency shift caused by an optical load P_o can be computed by substituting Eq. (23) into Eq. (18) giving

$$x = -\frac{\alpha_k S_2}{4N_0 \Delta} \left[n^* \sqrt{1 + \frac{2\eta_{pb} \eta P_o \tau_{\max}}{\Delta V_L n^*}} - n^* \right]. \quad (25)$$

We observe a linear relationship between T_{bb} and the frequency shift as seen in Figure 10. Note that for the experimental setup T_{bb} is very nearly proportional to P_o . The range of optical powers over which we measure the responsivity is small and therefore it is difficult to distinguish a $\sqrt{P_o}$ from a P_o dependence. A linear (or nearly linear) relationship has been observed by many groups and widely reported in the literature with no clear explanation of the phenomenon for both aluminum⁴³ and TiN devices.^{20,42} These other measurements tested over a wider range of optical power.

By taking the partial derivative of Eq. (25) with respect to P_o , we can compute the expected responsivity:

$$\frac{\partial x}{\partial P_o} = \frac{\alpha_k S_2 \tau_{\max} \eta_{pb} \eta}{4N_0 \Delta^2 V_L} \left[1 + \frac{2\eta_{pb} \eta P_o \tau_{\max}}{\Delta V_L n^*} \right]^{-1/2}. \quad (26)$$

Substituting in $\alpha_k = 0.65$, $S_2 = 3.8$, $V_L = 1870 \mu\text{m}^3$, $\eta_{pb} = 0.7$, $\eta = 0.14$, $\tau_{\max} = 500 \mu\text{s}$, $n^* = 400 \mu\text{m}^{-3}$, and $\nu = 150 \text{ GHz}$ yields $\partial x / \partial P_o \approx 45 \text{ ppm/pW}$. For a blackbody load temperature of 4 K, we expect $P_o \approx 1.75 \text{ pW}$ and $\delta P_o / \delta T_{bb} \approx 0.88 \text{ pW/K}$, which implies $\partial x / \partial T \approx 40 \text{ ppm/K}$, in good agreement with our measurements.

Alternatively, if $n^* = 160 \mu\text{m}^{-3}$, as would be the case if $\Delta = 1.92 k_B T_c$ (see Figure 8), $\eta = 0.32$ would also yield a responsivity of 40 ppm/K.

3. Optical versus thermal response

A comparison of the response to optical power and to changing bath temperature is presented in Figure 11. Mattis-Bardeen theory predicts that for a given change in quasiparticle density, the fractional change in resonant frequency should be very nearly linearly related to the change in the quality factor.⁴³ This behavior is evident in these devices. The slope of this linear relationship is the ratio of the frequency responsivity to the dissipation responsivity, and is defined in the literature as²¹

$$\beta = -\frac{2\delta f_0 / f_0}{\delta Q_r^{-1}} = \frac{S_2}{S_1} = \frac{1 + \sqrt{\frac{2\Delta}{\pi k_B T}} \exp\left(-\frac{hf}{2k_B T}\right) I_0\left(\frac{hf}{2k_B T}\right)}{\frac{2}{\pi} \sqrt{\frac{2\Delta}{\pi k_B T}} \sinh\left(\frac{hf}{2k_B T}\right) K_0\left(\frac{hf}{2k_B T}\right)}. \quad (27)$$

This quantity and the theoretical prediction are plotted in Figure 12.

Gao *et al.*⁴³ showed theoretically and experimentally that β should be the same for quasiparticles generated thermally or

FIG. 11. Resonant frequency shift plotted versus inverse quality factor for a single resonator, showing good agreement to the linear behavior predicted by Mattis-Bardeen theory. The points derived from bath temperature sweeps (blue dots and green triangles) show a consistent slope, which differs from that found when sweeping the blackbody load temperature (red crosses). The dashed lines are linear fits to the data, used to derive the β parameters plotted in Figure 12.

optically. Our measurements seem to show a different behavior. We find that β matches the theoretical prediction when changing the device temperature, either in a dark environment, or with a constant optical flux from the black body load held at a fixed temperature. However, when the bath temperature is kept fixed and the black body load temperature is varied, β is appreciably smaller. This effect has been reported for other devices as well.⁴⁴ They suggest that this effect could be explained if the optical pair breaking is non-uniform across the inductor. This could be the case for our devices: we designed them to efficiently couple to the circular waveguide, but electromagnetic simulations do show variations in the electric field of the incident millimeter wavelength radiation across the inductor. We plan to further investigate this phenomenon in the future.

4. Noise

Noise measurements were made by recording time series of the complex transmission at a fixed probe frequency. For

FIG. 12. Ratio of frequency responsivity over dissipation responsivity (β) plotted versus resonant frequency for all resonators. The thick line shows the theoretical curve expected for a thermal quasiparticle distribution, given by Eq. (27). The errors on all measurements are similar to those shown on the dark, T_{bath} sweep curve. The marker symbols and colors match the corresponding data in Figure 11, from which the values of β are derived.

each noise measurement, a frequency sweep was performed and fit to the resonator model given in Eq. (7) to determine the optimal value of the probe tone frequency. When analyzing the noise data, the complex time series is scaled by the complex dS_{21}/df vector determined from the resonator model. The real and imaginary components of the resulting scaled time series then correspond to the fluctuations in resonant frequency and dissipation, respectively. This also results in the units of the frequency fluctuation time stream being hertz. As a check, we also apply the eigenvector decomposition technique suggested by Gao *et al.*,²⁵ which reports a constant rotation angle between the two principal components of the fluctuation spectrum within the device bandwidth, thus confirming that the fluctuations can be decomposed using a simple rotation.

Initially, noise measurements were taken with the pulse-tube cooler on. This did not produce significant low-frequency noise when the devices were in a copper package, as the resonator quality factors were limited by the coupling to the lossy normal metal. However, when testing with the superconducting aluminum package, the larger Q_i increased the responsivity, and noise from the pulse-tube cooler was clearly evident in the noise spectrum. The spectra shown here were taken with the pulse-tube cooler off, while the ADR continued to regulate the temperature of the detector package. Turning off the pulse-tube cooler is not a viable option for a deployed instrument, so we are working to better understand and mitigate the source of this extra noise.

A series of noise spectra are shown in Figure 13 for load temperatures between 4 and 5.3 K. Figure 14 shows the result of averaging 13 spectra taken in succession with a fixed 4 K load temperature and 200 mK bath temperature to better show the quality of the noise at low frequencies. The measured $\text{Hz}/\sqrt{\text{Hz}}$ fluctuation spectrum is converted to $\mu\text{K}/\sqrt{\text{Hz}}$ units by multiplying by the slope of the measured frequency

FIG. 13. The noise spectrum of a single, typical detector is shown at different optical loads. The blackbody temperatures range from 4 K (purple) to 5.3 K (yellow), with the noise level increasing slightly with temperature. The average value in the region indicated near 100 Hz corresponds to the measurements shown in Figure 15. The probe tone power was approximately -105 dBm.

FIG. 14. The average spectrum (thick blue line) of a resonator obtained from 13 time series, each 30 s long. This is a different resonator than that shown in Figure 13. Multiple time series were taken to see the noise down to very low frequencies, which appears to be very flat. For modulation schemes, such as with a continuously rotating half-wave plate (HWP), that we envision for future CMB projects,^{1,2} we are particularly interested in the noise performance between 10 and 50 Hz. The thin red line is a fit of the spectrum to a Lorentzian model, showing good agreement. The resonator ring-down causes the roll-off at 460 Hz. The steep rise at the lowest frequencies is due to drift of the blackbody load temperature. The probe tone power for this measurement was approximately -113 dBm.

shift as a function of blackbody temperature, using the measurements shown in Figure 10. This can in turn be interpreted as noise equivalent temperature (NET) by dividing by $\sqrt{2} \sqrt{s}/\sqrt{\text{Hz}}$. The resonator in Figure 14 response rolls off at ~ 460 Hz. This bandwidth corresponds well with the expected half-width at half-maximum (HWHM) resonator bandwidth of $(f_0/Q_r)/2$, where, for this resonator, $f_0 = 92.277432$ MHz and $Q_r = 99595$. The high quality factor and low resonant frequency obscures the roll-off due to the quasiparticle lifetime τ_{qp} .

Using the semi-empirical model, we predicted the noise equivalent power (NEP) contributions for the LEKIDs in our cryogenic set up and then converted them to NET as shown in Figure 15. The photon noise is calculated as $\text{NEP}_{\text{photon}} = \sqrt{2\eta P_o h\nu(1+n_o)}/\eta$, where n_o is the photon occupancy number and is negligible for the range of powers tested.^{21,46} The absorption is expected to be high ($>70\%$) in the polarization for which the detectors were designed to be sensitive, which we refer to as η_1 . Additional optical loading may possibly couple into the detectors from the orthogonal polarization (η_2) or leaked power from adjacent resonators (η_{leakage}). For the plot in Figure 15, we used $\eta_1 = 0.72$, $\eta_2 = 0.13$, and $\eta_{\text{leakage}} = 0.075$, so $\eta = (\eta_1 + \eta_2)/2 + \eta_{\text{leakage}} = 0.5$. The expected generation-recombination noise can be approximated as $\text{NEP}_{GR} \approx \sqrt{2\eta P_o \Delta/\eta_{pb}}/\eta$, and should be the dominant detector noise source in the case of photon noise limited detectors.⁴⁷ The NET is calculated using $\text{NET} = \text{NEP}/(\sqrt{2} dP_o(T)/dT)$. We emphasize this is the NET at the load temperature in our experiment, not NET_{CMB} .

The optical efficiency of the detectors influences both the expected photon and g-r noise levels. Due to the uncertainty of the optical efficiency, we predict a range of a expected NET values for the detectors. For a photon noise limited detector, the predicted total detector NET value is approximately $20\text{--}30 \mu\text{K}\sqrt{s}$ at 2 pW of incident power. This predicted NET range

is for an optical efficiency range of $\eta = 0.3$ to 0.7 for a single mode with two polarizations.

As seen in Figure 16, the NET of the detectors on the tested array fall in the range $26 \pm 6 \mu\text{K}\sqrt{\text{s}}$ with a 4 K optical load. We estimate the random error on individual NET measurements to be $\sim 10\%$. We do not find any systematic relationship between NET and resonant frequency. Over the range of blackbody temperatures tested the noise remains fairly constant. However, as shown in Figure 16 the dependence of the noise on temperature is very shallow. The test setup was designed to directly measure the NET at 4 K using only small changes in load temperature. In future experiments, we will use another optical source to probe the noise over a wider range of optical power.

The predicted amplifier noise contribution in units of $\text{Hz}/\sqrt{\text{Hz}}$ is⁴⁸

$$e_{f,amp} = \sqrt{\frac{4k_B T_N}{P_{read}} \frac{Q_c}{Q_r^2} f_0}, \quad (28)$$

where $T_N \sim 4$ K is the noise temperature of the LNA and P_{read} is the probe tone power. While there is uncertainty in the exact value of P_{read} , the estimated value of -105 dBm predicts $e_{f,amp} \sim 0.05 \text{ Hz}/\sqrt{\text{Hz}}$ for $f_0 = 100$ MHz, in reasonable agreement with the measurements shown in Figure 13.

Given the uncertainty in our exact optical absorption and pair breaking efficiencies, the measured noise data shown in Figure 16 is consistent with our devices having a contribution from TLS noise at a level ranging from negligible to approximately equal to the photon noise level. We find the noise spectrum is white down to the lowest frequencies measured, as seen in Figure 14. This behavior has been reported by other groups,⁴⁹ however previous measurements of devices

FIG. 15. The predicted levels for the different noise sources versus optical power. The total NET is composed of photon noise and detector noise (under load). The detector noise includes three components: g-r noise, readout amplifier noise, and TLS noise. The expected TLS noise level is computed using a semiempirical formula²² and fiducial scaling values were provided by MAKO.¹³ The expected amplifier and TLS values are calculated assuming operation near bifurcation, which changes with load. The gray vertical lines correspond to blackbody load temperatures from 2 to 7 K in steps of 1 K.

FIG. 16. Measured NET values and the predicted NET range. The incident power at the horn aperture is calculated from the blackbody temperature T_{bb} using an emissivity of 0.92 for a single mode in two polarizations. The absorption efficiency of the detectors can be simulated but is unmeasured. The blue band shows the range of NETs expected for absorption efficiencies between $\eta = 0.3$ and $\eta = 0.7$. The stars show measured total NETs including the photon and detector noise. The data were measured with a constant probe tone power of approximately -105 dBm.

with TLS noise typically have a $e_{f,TLS} \sim \nu^{-0.25}$ shape, where ν is the frequency of the noise spectrum.¹³

IV. CONCLUSION

In this paper we presented a LEKID design and a horn-coupling strategy that appears promising for CMB studies. Our LEKIDs were made from a single thin aluminum film deposited on a silicon wafer and patterned using standard photolithographic techniques at STAR Cryoelectronics. We described the cryogenic testing apparatus and the testing program. Finally, we presented the results from our optical testing, dark testing and aluminum film characterization measurements. Our data were compared with Mattis-Bardeen theory for consistency. These results show the multiplexing scheme works well, the yield across multiple LEKID arrays is 91%, and the NETs are in the range $26 \pm 6 \mu\text{K}\sqrt{\text{s}}$.

Future work will focus on further decreasing the TLS effects, increasing the number of elements in the array, developing a dual-polarization design and better understanding the performance of these devices. In particular, the following items warrant further investigation: (i) the response of the detectors is somewhat more linear than expected, (ii) the measured β is different for thermal and optical quasiparticles, and (iii) the T_{bath} sweeps in Figure 7 show evidence for TLS effects but the relationship between δ_{TLS} and the TLS noise level is unknown, in particular for low-frequency, aluminum LEKIDs. We also plan to measure the noise of these devices over a wider range of optical power using an improved optical source.

We have already fabricated a second-generation wafer that underwent an hydrofluoric acid dip during fabrication, and we expect the TLS effects of the devices on this wafer will be reduced.

A small fraction of the radiation that is not absorbed or reflected propagates laterally in the dielectric substrates and this signal could produce detector-to-detector cross-talk. To mitigate this effect, we will metalize the fused silica wafer with titanium nitride (TiN) between the horns and patterned to act as an efficient millimeter-wave absorber with an effective sheet resistance of approximately 150 Ω . This TiN layer also helps to absorb ballistic phonons propagating in the silicon from energy deposited by cosmic rays. We are working with STAR Cryoelectronics on TiN films with the desired T_c . This work could also lead naturally to developing commercial TiN LEKID designs sensitive to different frequencies.

The present geometry of the inductor absorbs an average of less than 10% of the cross polarization as predicted by electromagnetic simulations. A rectangular waveguide or wire grid polarizer in front of the focal plane will further define the polarization selectivity of the focal plane, and make it truly single-polarization. We plan to add one of these varieties of polarization selectivity to future detector modules.

ACKNOWLEDGMENTS

This LEKID research is supported by a grant from the Research Initiatives for Science and Engineering (RISE) program at Columbia University to B.R.J., and by internal Columbia University funding to A.M. Matthew Underhill at the Micromachining Laboratory at Arizona State University machined the aluminum module with horns used for the measurements reported here. We thank the Xilinx University Program for their generous donation of FPGA hardware and software tools used in the readout system. We also thank the anonymous reviewer for helpful comments. This research has made use of NASA's Astrophysics Data System.

R.C. of STAR Cryoelectronics is a co-author and also owner of the foundry which fabricated the devices.

APPENDIX: ROOT OF THE BIFURCATION EQUATION

The root of the cubic equation that appears in the bifurcation resonator model relevant to the branch of the bifurcation accessible by our measurements is given by

$$y = y_0/3 + \frac{y_0^2/9 - 1/12}{k_1} + k_1, \quad (\text{A1})$$

where

$$k_1 = \sqrt[3]{a/8 + y_0/12 + k_2 + y_0^3/27} \quad (\text{A2})$$

and

$$k_2 = \sqrt{(y_0^3/27 + y_0/12 + a/8)^2 - (y_0^2/9 - 1/12)^3}. \quad (\text{A3})$$

See Swenson *et al.*³⁶ for a discussion of the branches of the bifurcation.

¹B. R. Johnson, P. A. R. Ade, D. Araujo, K. J. Bradford, D. Chapman, P. K. Day, J. Didier, S. Doyle, H. K. Eriksen, D. Flanigan, C. Groppi, S. Hillbrand, G. Jones, M. Limon, P. Mäuskopf, H. McCarrick, A. Miller, T. Mroczkowski, B. Reichborn-Kjennerud, B. Smiley, J. Sobrin, I. K. Wehus, and J. Zmuidzinas, *J. Low Temp. Phys.* **176**, 741 (2014).

²D. Araujo, P. A. R. Ade, J. R. Bond, K. J. Bradford, D. Chapman, G. Che, P. K. Day, J. Didier, S. Doyle, H. K. Eriksen, D. Flanigan, C. Groppi, S. N.

Hillbrand, B. R. Johnson, G. Jones, M. Limon, A. D. Miller, P. Mäuskopf, H. McCarrick, T. Mroczkowski, B. Reichborn-Kjennerud, B. Smiley, J. Sobrin, I. K. Wehus, and J. Zmuidzinas, *Proc. SPIE* **9153**, 91530W (2014).

³K. D. Irwin, and G. C. Hilton, in *Cryogenic Particle Detection*, Topics in Applied Physics, edited by C. Enss (Springer, Berlin, 2005), Vol. 99, pp. 63–150.

⁴Z. D. Kermish, P. Ade, A. Anthony, K. Arnold, D. Barron, D. Boettger, J. Borrill, S. Chapman, Y. Chinone, M. A. Dobbs, J. Errard, G. Fabbian, D. Flanigan, G. Fuller, A. Ghribi, W. Grainger, N. Halverson, M. Hasegawa, K. Hattori, M. Hazumi, W. L. Holzapfel, J. Howard, P. Hyland, A. Jaffe, B. Keating, T. Kisner, A. T. Lee, M. Le Jeune, E. Linder, M. Lungu, F. Matsuda, T. Matsumura, X. Meng, N. J. Miller, H. Morii, S. Moyerman, M. J. Myers, H. Nishino, H. Paar, E. Quealy, C. L. Reichardt, P. L. Richards, C. Ross, A. Shimizu, M. Shimon, C. Shimmmin, M. Sholl, P. Sirtanask, H. Spieler, N. Stebor, B. Steinbach, R. Stompor, A. Suzuki, T. Tomaru, C. Tucker, and O. Zahn, *Proc. SPIE* **8452**, 84521C (2012); e-print [arXiv:1210.7768](https://arxiv.org/abs/1210.7768) [astro-ph.IM].

⁵R. W. I. Ogburn, P. A. R. Ade, R. W. Aikin, M. Amiri, S. J. Benton, J. J. A. P. Bock, J. A. Bonetti, J. A. Brevik, B. Burger, C. D. Dowell, L. Duband, J. P. Filippini, S. R. Golwala, M. Halpern, M. Hasselfield, G. C. Hilton, V. V. Hristov, K. D. Irwin, J. P. Kaufman, B. G. Keating, J. M. Kovac, C. L. Kuo, A. E. Lange, E. M. Leitch, C. B. Netherfield, H. T. Nguyen, A. Orlando, C. L. Pryke, C. Reintsema, S. Richter, J. E. Ruhl, M. C. Runyan, C. D. Sheehy, Z. K. Staniszewski, S. A. Stokes, R. V. Sudiwala, G. P. Teply, J. E. Tolan, A. D. Turner, P. Wilson, and C. L. Wong, *Proc. SPIE* **7741**, 77411G (2010).

⁶E. M. George, P. Ade, K. A. Aird, J. E. Austermann, J. A. Beall, D. Becker, A. Bender, B. A. Benson, L. E. Bleem, J. Britton, J. E. Carlstrom, C. L. Chang, H. C. Chiang, H.-M. Cho, T. M. Crawford, A. T. Crites, A. Datesman, T. de Haan, M. A. Dobbs, W. Everett, A. Ewall-Wice, N. W. Halverson, N. Harrington, J. W. Henning, G. C. Hilton, W. L. Holzapfel, S. Hoover, N. Huang, J. Hubmayr, K. D. Irwin, M. Karfunkle, R. Keisler, J. Kennedy, A. T. Lee, E. Leitch, D. Li, M. Lueker, D. P. Marrone, J. J. McMahon, J. Mehl, S. S. Meyer, J. Montgomery, T. E. Montroy, J. Nagy, T. Natoli, J. P. Nibarger, M. D. Niemack, V. Novosad, S. Padin, C. Pryke, C. L. Reichardt, J. E. Ruhl, B. R. Saliwanchik, J. T. Sayre, K. K. Schaffer, E. Shirokoff, K. Story, C. Tucker, K. Vanderlinde, J. D. Vieira, G. Wang, R. Williamson, V. Yefremenko, K. W. Yoon, and E. Young, *Proc. SPIE* **8452**, 84521F (2012); e-print [arXiv:1210.4971](https://arxiv.org/abs/1210.4971) [astro-ph.IM].

⁷B. Reichborn-Kjennerud, A. M. Aboobaker, P. Ade, F. Aubin, C. Baccigalupi, C. Bao, J. Borrill, C. Cantalupo, D. Chapman, J. Didier, M. Dobbs, J. Grain, W. Grainger, S. Hanany, S. Hillbrand, J. Hubmayr, A. Jaffe, B. Johnson, T. Jones, T. Kisner, J. Klein, A. Korotkov, S. Leach, A. Lee, L. Levinson, M. Limon, K. MacDermid, T. Matsumura, X. Meng, A. Miller, M. Milligan, E. Pascale, D. Polsgrove, N. Ponthieu, K. Raach, I. Sagiv, G. Smecher, F. Stivoli, R. Stompor, H. Tran, M. Tristram, G. S. Tucker, Y. Vinokurov, A. Yadav, M. Zalzarriaga, and K. Zilic, *Proc. SPIE* **7741**, 77411C (2010); e-print [arXiv:1007.3672](https://arxiv.org/abs/1007.3672) [astro-ph.CO].

⁸D. Schwan, P. A. R. Ade, K. Basu, A. N. Bender, F. Bertoldi, H.-M. Cho, G. Chon, J. Clarke, M. A. Dobbs, D. Ferrusca, R. Guesten, N. W. Halverson, W. L. Holzapfel, C. Horellou, D. Johansson, B. R. Johnson, J. Kennedy, Z. Kermish, R. Kneissl, T. M. Lanting, A. T. Lee, M. Lueker, J. Mehl, K. M. Menten, D. Muters, F. Pacaud, T. Plagege, C. L. Reichardt, P. L. Richards, R. Schaaf, P. Schilke, M. W. Sommer, H. G. Spieler, C. Tucker, A. Weiss, B. Westbrook, and O. Zahn, *Rev. Sci. Instrum.* **82**, 091301 (2011).

⁹M. D. Niemack, P. A. R. Ade, J. Aguirre, F. Barrientos, J. A. Beall, J. R. Bond, J. Britton, H. M. Cho, S. Das, M. J. Devlin, S. Dicker, J. Dunkley, R. Dünner, J. W. Fowler, A. Hajian, M. Halpern, M. Hasselfield, G. C. Hilton, M. Hilton, J. Hubmayr, J. P. Hughes, L. Infante, K. D. Irwin, N. Jarosik, J. Klein, A. Kosowsky, T. A. Marriage, J. McMahon, F. Menanteau, K. Moodley, J. P. Nibarger, M. R. Nolte, L. A. Page, B. Partridge, E. D. Reese, J. Sievers, D. N. Spergel, S. T. Staggs, R. Thornton, C. Tucker, E. Wollack, and K. W. Yoon, *Proc. SPIE* **7741**, 77411S (2010); e-print [arXiv:1006.5049](https://arxiv.org/abs/1006.5049) [astro-ph.IM].

¹⁰P. K. Day, H. G. LeDuc, B. A. Mazin, A. Vayonakis, and J. Zmuidzinas, *Nature (London)* **425**, 817 (2003).

¹¹S. Doyle, P. Mäuskopf, J. Naylon, A. Porch, and C. Duncombe, *J. Low Temp. Phys.* **151**, 530 (2008).

¹²B. A. Mazin, S. R. Meeker, M. J. Strader, P. Szypryt, D. Marsden, J. C. van Eyken, G. E. Duggan, A. B. Walter, G. Ulbricht, M. Johnson, B. Bumble, K. O' Brien, and C. Stoughton, *Publ. Astron. Soc. Pac.* **125**, 1348 (2013); e-print [arXiv:1306.4674](https://arxiv.org/abs/1306.4674) [astro-ph.IM].

¹³C. McKenney, H. G. LeDuc, L. J. Swenson, P. K. Day, B. H. Eom, and J. Zmuidzinas, *Proc. SPIE* **8452**, 84520S (2012).

- ¹⁴A. Patel, A. Brown, W. Hsieh, T. Stevenson, S. Moseley, K. U-yen, N. Ehsan, E. Barrentine, G. Manos, and E. Wollack, *IEEE Trans. Appl. Supercond.* **23**, 2400404 (2013).
- ¹⁵S. R. Golwala, C. Bockstiegel, S. Brugger, N. G. Czakon, P. K. Day, T. P. Downes, R. Duan, J. Gao, A. K. Gill, J. Glenn, M. I. Hollister, H. G. LeDuc, P. R. Maloney, B. A. Mazin, S. G. McHugh, D. Miller, O. Noroozian, H. T. Nguyen, J. Sayers, J. A. Schlaerth, S. Siegel, A. K. Vayonakis, P. R. Wilson, and J. Zmuidzinas, *Proc. SPIE* **8452**, 845205 (2012).
- ¹⁶A. Monfardini, A. Benoit, A. Bideaud, L. Swenson, A. Cruciani, P. Camus, C. Hoffmann, F. X. Désert, S. Doyle, P. Ade, P. Mauskopf, C. Tucker, M. Roesch, S. Leclercq, K. F. Schuster, A. Endo, A. Baryshev, J. J. A. Baselmans, L. Ferrari, S. J. C. Yates, O. Bourrion, J. Macias-Perez, C. Vescovi, M. Calvo, and C. Giordano, *Astrophys. J. Suppl.* **194**(2), 24 (2011); e-print [arXiv:1102.0870](https://arxiv.org/abs/1102.0870) [astro-ph.IM].
- ¹⁷B. J. Dober, P. A. R. Ade, P. Ashton, F. E. Angilè, J. A. Beall, D. Becker, K. J. Bradford, G. Che, H.-M. Cho, M. J. Devlin, L. M. Fissel, Y. Fukui, N. Galitzki, J. Gao, C. E. Groppi, S. Hillbrand, G. C. Hilton, J. Hubmayr, K. D. Irwin, J. Klein, J. Van Lanen, D. Li, Z.-Y. Li, N. P. Lourie, H. Mani, P. G. Martin, P. Mauskopf, F. Nakamura, G. Novak, D. P. Pappas, E. Pascale, F. P. Santos, G. Savini, D. Scott, S. Stanchfield, J. N. Ullom, M. Underhill, M. R. Visser, and D. Ward-Thompson, *Proc. SPIE* **9153**, 91530H (2014); e-print [arXiv:1407.3756](https://arxiv.org/abs/1407.3756) [astro-ph.IM].
- ¹⁸A. Kovács, P. S. Barry, C. M. Bradford, G. Chattopadhyay, P. Day, S. Doyle, S. Hailey-Dunsheath, M. Hollister, C. McKenney, H. G. LeDuc, N. Llombart, D. P. Marrone, P. Mauskopf, R. C. O'Brien, S. Padin, L. J. Swenson, and J. Zmuidzinas, *Proc. SPIE* **8452**, 84522G (2012); e-print [arXiv:1211.0934](https://arxiv.org/abs/1211.0934) [astro-ph.IM].
- ¹⁹P. Mauskopf, S. Doyle, P. Barry, S. Rowe, A. Bidead, P. Ade, C. Tucker, E. Castillo, A. Monfardini, J. Goupy, and M. Calvo, *J. Low Temp. Phys.* **176**(3–4), 545–552 (2014).
- ²⁰J. Hubmayr, J. Beall, D. Becker, H.-M. Cho, M. Devlin, B. Dober, C. Groppi, G. C. Hilton, K. D. Irwin, D. Li, P. Mauskopf, D. P. Pappas, J. Van Lanen, M. R. Visser, and J. Gao, preprint [arXiv:1406.4010](https://arxiv.org/abs/1406.4010) [astro-ph.IM] (2014).
- ²¹J. Zmuidzinas, *Annu. Rev. Condens. Matter Phys.* **3**, 169 (2012).
- ²²J. Gao, M. Daal, J. M. Martinis, A. Vayonakis, J. Zmuidzinas, B. Sadoulet, B. A. Mazin, P. K. Day, and H. G. LeDuc, *Appl. Phys. Lett.* **92**, 212504 (2008); e-print [arXiv:0804.0467](https://arxiv.org/abs/0804.0467) [cond-mat.supr-con].
- ²³S. Doyle, “Lumped element kinetic inductance detectors,” Ph.D. thesis (Cardiff University, 2008).
- ²⁴M. Tinkham, *Introduction to Superconductivity*, 2nd ed. (Dover Publications, 2004).
- ²⁵J. Gao, J. Zmuidzinas, B. A. Mazin, H. G. LeDuc, and P. K. Day, *Appl. Phys. Lett.* **90**, 102507 (2007); e-print [arXiv:cond-mat/0609614](https://arxiv.org/abs/cond-mat/0609614).
- ²⁶J. Gao, M. Daal, A. Vayonakis, S. Kumar, J. Zmuidzinas, B. Sadoulet, B. A. Mazin, P. K. Day, and H. G. LeDuc, *Appl. Phys. Lett.* **92**, 152505 (2008); e-print [arXiv:0802.4457](https://arxiv.org/abs/0802.4457) [cond-mat.supr-con].
- ²⁷Y. C. Lim and R. Moore, *IEEE Trans. Electron Devices* **15**, 173 (1968).
- ²⁸S. Weinreb, J. C. Bardin, and H. Mani, *IEEE Trans. Microwave Theory Tech.* **55**, 2306 (2007).
- ²⁹See <http://www.coax.co.jp/english> for information about the superconducting coax used in this experiment.
- ³⁰A. Kushino, S. Kasai, S. Kohjiro, S. Shiki, and M. Ohkubo, *J. Low Temp. Phys.* **151**, 650 (2008).
- ³¹See <http://casper.berkeley.edu> for a description of the CASPER tools and hardware.
- ³²R. Duan, S. McHugh, B. Serfass, B. A. Mazin, A. Merrill, S. R. Golwala, T. P. Downes, N. G. Czakon, P. K. Day, J. Gao, J. Glenn, M. I. Hollister, H. G. LeDuc, P. R. Maloney, O. Noroozian, H. T. Nguyen, J. Sayers, J. A. Schlaerth, S. Siegel, J. E. Vaillancourt, A. Vayonakis, P. R. Wilson, and J. Zmuidzinas, *Proc. SPIE* **7741**, 77411V (2010).
- ³³See https://github.com/ColumbiaCMB/kid_readout for the source code for the readout system used in this experiment.
- ³⁴J. B. Peterson and P. L. Richards, *Int. J. Infrared Millimeter Waves* **5**, 1507 (1984).
- ³⁵R. Meserve and P. M. Tedrow, *J. Appl. Phys.* **42**, 51 (1971).
- ³⁶L. J. Swenson, P. K. Day, B. H. Eom, H. G. LeDuc, N. Llombart, C. M. McKenney, O. Noroozian, and J. Zmuidzinas, *J. Appl. Phys.* **113**, 104501 (2013).
- ³⁷M. S. Khalil, M. J. A. Stoutimore, F. C. Wellstood, and K. D. Osborn, *J. Appl. Phys.* **111**, 054510 (2012).
- ³⁸See <http://cars9.uchicago.edu/software/python/lmfit> for information about the lmfit Python package.
- ³⁹D. Foreman-Mackey, D. W. Hogg, D. Lang, and J. Goodman, *Publ. Astron. Soc. Pac.* **125**, 306 (2013); e-print [arXiv:1202.3665](https://arxiv.org/abs/1202.3665) [astro-ph.IM].
- ⁴⁰See <http://www.alcoaql10.com> for information about the QC-10 aluminium alloy used in this experiment.
- ⁴¹L. J. Swenson, P. K. Day, C. D. Dowell, B. H. Eom, M. I. Hollister, R. Jarnot, A. Kovacs, H. G. LeDuc, C. M. McKenney, R. Monroe, T. Mroczkowski, H. T. Nguyen, and J. Zmuidzinas, *Proc. SPIE* **8452**, 84520P (2012).
- ⁴²O. Noroozian, “Superconducting microwave resonator arrays for submillimeter/far-infrared imaging,” Ph.D. thesis (California Institute of Technology, 2012).
- ⁴³J. Gao, J. Zmuidzinas, A. Vayonakis, P. Day, B. Mazin, and H. LeDuc, *J. Low Temp. Phys.* **151**, 557 (2008).
- ⁴⁴R. M. J. Janssen, A. Endo, P. J. de Visser, T. M. Klapwijk, and J. J. A. Baselmans, *Appl. Phys. Lett.* **105**, 193504 (2014).
- ⁴⁵T. Guruswamy, D. J. Goldie, and S. Withington, *Supercond. Sci. Technol.* **27**, 055012 (2014); e-print [arXiv:1401.1937](https://arxiv.org/abs/1401.1937) [cond-mat.supr-con].
- ⁴⁶P. J. de Visser, J. J. A. Baselmans, J. Bueno, N. Llombart, and T. M. Klapwijk, *Nat. Commun.* **5**, 3130 (2014); e-print [arXiv:1306.4238](https://arxiv.org/abs/1306.4238) [cond-mat.supr-con].
- ⁴⁷S. J. C. Yates, J. J. A. Baselmans, A. Endo, R. M. J. Janssen, L. Ferrari, P. Diener, and A. Baryshev, *Appl. Phys. Lett.* **99**, 073505 (2011).
- ⁴⁸T. H. Lee and A. Hajimiri, *IEEE J. Solid-State Circuits* **35**, 326 (2000).
- ⁴⁹E. Shirokoff, P. Barry, C. Bradford, G. Chattopadhyay, P. Day, S. Doyle, S. Hailey-Dunsheath, M. Hollister, A. Kovács, H. LeDuc, C. McKenney, P. Mauskopf, H. Nguyen, R. O'Brien, S. Padin, T. Reck, L. Swenson, C. Tucker, and J. Zmuidzinas, *J. Low Temp. Phys.* **176**, 657 (2014).